			[1.05 [26.67]	2.10 53.34] .50 [12.71] SUM (+)	•
	г	1.05 26.67]	- (+)	$( \div )$	2.10 [53.34]
	.10	[2.54]_		2 ⊕ 6X Ø.150	
	.1	10 [2.54] → .55 [13.94] <sup>-</sup>		1.00 25.40] [ø3.81] Mounting Holes N Connectors 3 Places	
Electrical:	Specific	.55 [13.94] <sup>-</sup>		Mounting Holes 1.00 25.40] N Connectors 3 Places	423 Black Oak Ridge Rd. Wayne, NJ 07470
Frequency Range:	<b>Specific</b> 800-1000	.55 [13.94] <sup>-</sup>	Mhz	1.00 N Connectors	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435
Frequency Range:	.1 Specific 800-1000 0.3	.55 [13.94] <sup>-</sup>	Mhz Max	Mounting Holes 1.00 25.40] N Connectors 3 Places	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: nsertion Loss: Amplitude Balance:	Specific 800-1000 0.3 0.2	.55 [13.94] <sup>-</sup> ations: dB dB	Mhz Max Max	Mounting Holes 1.00 25.40] N Connectors 3 Places SigaTek	Wayne, NJ 07470   Ph: 973-706-8475, Fax: 973-832-4435   www.sigatek.com   2-way Power Combiner
Frequency Range: Insertion Loss: Amplitude Balance: Isolation:	5 <b>Specific</b> 800-1000 0.3 0.2 25	.55 [13.94] <sup>-</sup> ations: dB dB dB dB	Mhz Max Max Min	Mounting Holes 1.00 25.40] N Connectors 3 Places SP25223N	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com
Frequency Range: Insertion Loss: Amplitude Balance: Isolation: Phase Balance:	.1 <b>Specific</b> 800-1000 0.3 0.2 25 4	.55 [13.94] <sup>-</sup> ations: dB dB	Mhz Max Max Min Max	Mounting Holes 1.00 25.40] N Connectors 3 Places Spaces Spaces Dimensions are in inches and (mm)	Wayne, NJ 07470   Ph: 973-706-8475, Fax: 973-832-4435   www.sigatek.com   2-way Power Combiner
Frequency Range: Insertion Loss: Amplitude Balance: Isolation: Phase Balance: VSWR Input:	.1 Specific 800-1000 0.3 0.2 25 4 1.20:1	.55 [13.94] <sup>-</sup> ations: dB dB dB dB	Mhz Max Max Min Max Max Max	Mounting Holes 1.00 25.40] N Connectors 3 Places Spaces Spaces Dimensions are in inches and (mm) Decimal Tolerance:	Wayne, NJ 07470   Ph: 973-706-8475, Fax: 973-832-4435   www.sigatek.com   2-way Power Combiner   N-Connectors
Frequency Range: Insertion Loss: Amplitude Balance: Isolation: Phase Balance: VSWR Input: VSWR Output:	.1 <b>Specific</b> 800-1000 0.3 0.2 25 4 1.20:1 1.20:1	.55 [13.94] <sup>-</sup> ations: dB dB dB dB Deg.	Mhz Max Max Min Max Max Max Max	Mounting Holes 1.00 25.40] N Connectors 3 Places SP25223N Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020	Wayne, NJ 07470   Ph: 973-706-8475, Fax: 973-832-4435   www.sigatek.com   2-way Power Combiner
Frequency Range: Insertion Loss: Amplitude Balance: Isolation: Phase Balance: VSWR Input: VSWR Output: Power at SUM port:	5 <b>Specific</b> 800-1000 0.3 0.2 25 4 1.20:1 1.20:1 100	.55 [13.94] <sup>-</sup> ations: dB dB dB dB Deg. Watt	Mhz Max Max Min Max Max Max Max Max	Mounting Holes 1.00 25.40] N Connectors 3 Places Spaces Spaces Dimensions are in inches and (mm) Decimal Tolerance:	Wayne, NJ 07470   Ph: 973-706-8475, Fax: 973-832-4435   www.sigatek.com   2-way Power Combiner   N-Connectors
Frequency Range: nsertion Loss: Amplitude Balance: solation: Phase Balance: /SWR Input: /SWR Output:	.1 <b>Specific</b> 800-1000 0.3 0.2 25 4 1.20:1 1.20:1	.55 [13.94] <sup>-</sup> ations: dB dB dB dB Deg.	Mhz Max Max Min Max Max Max Max	Mounting Holes 1.00 25.40] N Connectors 3 Places SP25223N Dimensions are in inches and (mm) Decimal Tolerance: 2 place +- 0.020	Wayne, NJ 07470 Ph: 973-706-8475, Fax: 973-832-4435 www.sigatek.com 2-way Power Combiner N-Connectors CAGE CODE : 69UC1