

# **CLASS V, 14-BIT, 105-MSPS ANALOG-TO-DIGITAL CONVERTER**

## **1 FEATURES**

- 14-Bit Resolution
- 105-MSPS Maximum Sample Rate
- SNR = 70 dBc at 105 MSPS and 50 MHz IF
- SFDR = 78 dBc at 105 MSPS and 50 MHz IF
- 2.2- $V_{PP}$  Differential Input Range
- 5-V Supply Operation
- 3.3-V CMOS Compatible Outputs
- 2.3-W Total Power Dissipation
- 2s Complement Output Format
- On-Chip Input Analog Buffer, Track and Hold, and Reference Circuit
- 52-Pin Ceramic Nonconductive Tie-Bar Package (HFG)

- Military Temperature Range  
( $-55^{\circ}\text{C}$  to  $125^{\circ}\text{C}$   $T_{case}$ )
- QML-V Qualified, SMD 5962-07206

## **2 APPLICATIONS**

- Single and Multichannel Digital Receivers
- Base Station Infrastructure
- Instrumentation
- Video and Imaging
- Engineering Evaluation (/EM) Samples are Available <sup>(1)</sup>

## **3 RELATED DEVICES**

- Clocking: CDC7005
- Amplifiers: OPA695, THS4509

(1) These units are intended for engineering evaluation only. They are processed to a non-compliant flow (e.g. No Burn-In, etc.) and are tested to a temperature rating of  $25^{\circ}\text{C}$  only. These units are not suitable for qualification, production, radiation testing or flight use. Parts are not warranted for performance over the full MIL specified temperature range of  $-55^{\circ}\text{C}$  to  $125^{\circ}\text{C}$  or operating life.

## **4 DESCRIPTION**

The ADS5424 is a 14-bit, 105-MSPS analog-to-digital converter (ADC) that operates from a 5-V supply, while providing 3.3-V CMOS compatible digital outputs. The ADS5424 input buffer isolates the internal switching of the on-chip track and hold (T&H) from disturbing the signal source. An internal reference generator is also provided to further simplify the system design. The ADS5424 has outstanding low noise and linearity, over input frequency. With only a 2.2- $V_{PP}$  input range, ADS5424 simplifies the design of multicarrier applications, where the carriers are selected on the digital domain.

The ADS5424 is available in a 52-pin ceramic nonconductive tie-bar package (HFG). The ADS5424 is built on state of the art Texas Instruments complementary bipolar process (BiCom3) and is specified over full military temperature range ( $-55^{\circ}\text{C}$  to  $125^{\circ}\text{C}$   $T_{case}$ ).






This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

## FUNCTIONAL BLOCK DIAGRAM



#### 4.1 ABSOLUTE MAXIMUM RATINGS

over operating temperature range (unless otherwise noted)<sup>(1)</sup>

|                                |  | ADS5424                           | UNIT |
|--------------------------------|--|-----------------------------------|------|
| Supply voltage                 | AV <sub>DD</sub> to GND                        | 6                                 | V    |
|                                | DRV <sub>DD</sub> to GND                       | 5                                 |      |
| Analog input to GND            |  | −0.3 V to AV <sub>DD</sub> + 0.3  | V    |
| Clock input to GND             |  | −0.3 V to AV <sub>DD</sub> + 0.3  | V    |
| CLK to $\overline{\text{CLK}}$ |  | ±2.5                              | V    |
| Digital data output to GND     |  | −0.3 V to DRV <sub>DD</sub> + 0.3 | V    |
| T <sub>C</sub>                 | Characterized case operating temperature range | −55°C to 125                      | °C   |
| T <sub>J</sub>                 | Maximum junction temperature                   | 150                               | °C   |
| T <sub>stg</sub>               | Storage temperature range                      | −65°C to 150                      | °C   |

(1) Stresses above these ratings may cause permanent damage. Exposure to absolute maximum conditions for extended periods may degrade device reliability. These are stress ratings only and functional operation of the device at these or any other conditions beyond those specified is not implied.

## 4.2 RECOMMENDED OPERATING CONDITIONS

|   | MIN  | NOM | MAX  | UNIT     |
|---|------|-----|------|----------|
| <b>SUPPLIES</b>                         |      |     |      |          |
| $AV_{DD}$ Analog supply voltage         | 4.75 | 5   | 5.25 | V        |
| $DRV_{DD}$ Output driver supply voltage | 3    | 3.3 | 3.6  | V        |
| <b>ANALOG INPUT</b>                     |      |     |      |          |
| Differential input range                |      | 2.2 |      | $V_{PP}$ |
| $V_{CM}$ Input common mode voltage      |      | 2.4 |      | V        |
| <b>DIGITAL OUTPUT</b>                   |      |     |      |          |
| Maximum output load                     |      | 10  |      | pF       |
| <b>CLOCK INPUT</b>                      |      |     |      |          |
| ADCLK input sample rate (sine wave)     | 30   |     | 105  | MSPS     |
| Clock amplitude, differential sine wave |      | 3   |      | $V_{PP}$ |
| Clock duty cycle                        |      | 50% |      |          |
| $T_C$ Open case temperature range       | –55  |     | 125  | °C       |

## 4.3 ELECTRICAL CHARACTERISTICS (Unchanged after 100 kRad)

Typical values at  $T_C = 25^\circ\text{C}$ . Over full temperature range is  $T_{C,MIN} = -55^\circ\text{C}$  to  $T_{C,MAX} = 125^\circ\text{C}$ , sampling rate = 105 MSPS, 50% clock duty cycle,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$ , –1 dBFS differential input, and 3- $V_{PP}$  sinusoidal clock (unless otherwise noted)

| PARAMETER                                | TEST CONDITIONS  | MIN   | TYP       | MAX  | UNIT       |
|--|--|-------|-----------|------|------------|
| Resolution                               |  |       | 14        |      | Bits       |
| <b>ANALOG INPUTS</b>                     |  |       |           |      |            |
| Differential input range                 |  |       | 2.2       |      | $V_{PP}$   |
| Differential input resistance            | See Figure 11  |       | 1         |      | k $\Omega$ |
| Differential input capacitance           | See Figure 11  |       | 1.5       |      | pF         |
| Analog input bandwidth                   |  |       | 570       |      | MHz        |
| <b>INTERNAL REFERENCE VOLTAGES</b>       |  |       |           |      |            |
| $V_{REF}$ Reference voltage              |  | 2.38  | 2.4       | 2.41 | V          |
| <b>DYNAMIC ACCURACY</b>                  |  |       |           |      |            |
| No missing codes                         |  |       | Tested    |      |            |
| DNL Differential linearity error         | $f_{IN} = 10\text{ MHz}$   | –0.98 | $\pm 0.5$ | 1.5  | LSB        |
| INL Integral linearity error             | $f_{IN} = 10\text{ MHz}$ $T_C = 25^\circ\text{C}$ and $T_{C,MAX}$  | –5.0  | $\pm 3.0$ | +5.0 | LSB        |
|  | $f_{IN} = 10\text{ MHz}$ $T_C = T_{C,MIN}$   | –6.9  |           | +6.9 | LSB        |
| Offset error                             |  | –1.5  | 0         | 1.5  | %FS        |
| Offset temperature coefficient           |  |       | 0.0007    |      | %FS/°C     |
| Gain error                               |  | –5    | 0.9       | 5    | %FS        |
| Gain temperature coefficient             |  |       | 0.006     |      | %FS/°C     |
| <b>POWER SUPPLY</b>                      |  |       |           |      |            |
| $I_{AVDD}$ Analog supply current         | $V_{IN} = \text{full scale}$ , $f_{IN} = 70\text{ MHz}$ $F_S = 105\text{ MSPS}$                                |       | 355       | 410  | mA         |
| $I_{DRVDD}$ Output buffer supply current | $V_{IN} = \text{full scale}$ , $f_{IN} = 70\text{ MHz}$ $F_S = 105\text{ MSPS}$                                |       | 47        | 55   | mA         |
| Power dissipation                        | Total power with 10-pF load on each digital output to ground, $f_{IN} = 70\text{ MHz}$ $F_S = 105\text{ MSPS}$ |       | 1.9       | 2.3  | W          |
| Power-up time                            | $F_S = 105\text{ MSPS}$  |       | 20        |      | ms         |

## ELECTRICAL CHARACTERISTICS (Unchanged after 100 kRad) (continued)

Typical values at  $T_C = 25^\circ\text{C}$ , Over full temperature range is  $T_{C,\text{MIN}} = -55^\circ\text{C}$  to  $T_{C,\text{MAX}} = 125^\circ\text{C}$ , sampling rate = 105 MSPS, 50% clock duty cycle,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$ ,  $-1\text{ dBFS}$  differential input, and  $3\text{-}V_{PP}$  sinusoidal clock (unless otherwise noted)

| PARAMETER                         |                              | TEST CONDITIONS           | MIN                      | TYP  | MAX  | UNIT |
|-----------------------------------|------------------------------|---------------------------|--------------------------|------|------|------|
| <b>DYNAMIC AC CHARACTERISTICS</b> |                              |                           |                          |      |      |      |
| SNR                               | Signal-to-noise ratio        | $f_{IN} = 10\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 70.5 | 72.4 | dBc  |
|                                   |                              |                           | $T_C = T_{C,\text{MAX}}$ | 71.0 |      |      |
|                                   |                              |                           | $T_C = T_{C,\text{MIN}}$ | 70.5 |      |      |
|                                   |                              | $f_{IN} = 30\text{ MHz}$  | Full Temp Range          | 70.0 | 71.5 |      |
|                                   |                              | $f_{IN} = 50\text{ MHz}$  |                          |      | 70.9 |      |
|                                   |                              | $f_{IN} = 70\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 68.2 | 70.1 |      |
|                                   |                              |                           | $T_C = T_{C,\text{MAX}}$ | 67.0 |      |      |
|                                   |                              |                           | $T_C = T_{C,\text{MIN}}$ | 68.0 |      |      |
|                                   |                              | $f_{IN} = 100\text{ MHz}$ |                          |      | 68.9 |      |
|                                   |                              | $f_{IN} = 170\text{ MHz}$ |                          |      | 66.3 |      |
| SFDR                              | Spurious free dynamic range  | $f_{IN} = 10\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 72.0 | 81.6 | dBc  |
|                                   |                              |                           | Full Temp Range          | 71.0 |      |      |
|                                   |                              | $f_{IN} = 30\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 77.0 | 80.6 |      |
|                                   |                              |                           | $T_C = T_{C,\text{MAX}}$ | 69.0 |      |      |
|                                   |                              |                           | $T_C = T_{C,\text{MIN}}$ | 75.0 |      |      |
|                                   |                              | $f_{IN} = 50\text{ MHz}$  |                          |      | 78.1 |      |
|                                   |                              | $f_{IN} = 70\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 68.0 | 82.6 |      |
|                                   |                              |                           | $T_C = T_{C,\text{MAX}}$ | 69.0 |      |      |
|                                   |                              |                           | $T_C = T_{C,\text{MIN}}$ | 67.0 |      |      |
|                                   |                              | $f_{IN} = 100\text{ MHz}$ |                          |      | 82.5 |      |
| SINAD                             | Signal-to-noise + distortion | $f_{IN} = 10\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 68.6 | 71.3 | dBc  |
|                                   |                              |                           | $T_C = T_{C,\text{MAX}}$ | 68.3 |      |      |
|                                   |                              |                           | $T_C = T_{C,\text{MIN}}$ | 68.2 |      |      |
|                                   |                              | $f_{IN} = 30\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 69.4 | 70.2 |      |
|                                   |                              |                           | $T_C = T_{C,\text{MAX}}$ | 67.0 |      |      |
|                                   |                              |                           | $T_C = T_{C,\text{MIN}}$ | 69.4 |      |      |
|                                   |                              | $f_{IN} = 50\text{ MHz}$  |                          |      | 69.9 |      |
|                                   |                              | $f_{IN} = 70\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 65.8 | 69.7 |      |
|                                   |                              |                           | $T_C = T_{C,\text{MAX}}$ | 64.6 |      |      |
|                                   |                              |                           | $T_C = T_{C,\text{MIN}}$ | 65.0 |      |      |
|                                   |                              | $f_{IN} = 100\text{ MHz}$ |                          |      | 68.6 |      |
|                                   |                              | $f_{IN} = 170\text{ MHz}$ |                          |      | 64.0 |      |
|                                   |                              | $f_{IN} = 230\text{ MHz}$ |                          |      | 61.1 |      |

## ELECTRICAL CHARACTERISTICS (Unchanged after 100 kRad) (continued)

Typical values at  $T_C = 25^\circ\text{C}$ , Over full temperature range is  $T_{C,\text{MIN}} = -55^\circ\text{C}$  to  $T_{C,\text{MAX}} = 125^\circ\text{C}$ , sampling rate = 105 MSPS, 50% clock duty cycle,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$ ,  $-1\text{ dBFS}$  differential input, and  $3\text{-}V_{PP}$  sinusoidal clock (unless otherwise noted)

| PARAMETER |  | TEST CONDITIONS           | MIN                      | TYP  | MAX  | UNIT |
|-----------|--|---------------------------|--------------------------|------|------|------|
| HD2       | Second harmonic                                    | $f_{IN} = 10\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 72.0 | 81.8 | dBc  |
|           |  |                           | Full Temp Range          | 71.0 |      |      |
|           |  | $f_{IN} = 30\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 77.0 | 80.6 |      |
|           |  |                           | $T_C = T_{C,\text{MAX}}$ | 69.0 |      |      |
|           |  |                           | $T_C = T_{C,\text{MIN}}$ | 75.0 |      |      |
|           |  | $f_{IN} = 50\text{ MHz}$  |                          | 86.5 |      |      |
|           |  | $f_{IN} = 70\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 68.0 | 85.0 |      |
|           |  |                           | $T_C = T_{C,\text{MAX}}$ | 69.0 |      |      |
|           |  |                           | $T_C = T_{C,\text{MIN}}$ | 67.0 |      |      |
|           |  | $f_{IN} = 100\text{ MHz}$ |                          | 86.1 |      |      |
|           |  | $f_{IN} = 170\text{ MHz}$ |                          | 93.0 |      |      |
|           |  | $f_{IN} = 230\text{ MHz}$ |                          | 71.0 |      |      |
| HD3       | Third harmonic                                     | $f_{IN} = 10\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 72.0 | 81.6 | dBc  |
|           |  |                           | Full Temp Range          | 71.0 |      |      |
|           |  | $f_{IN} = 30\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 77.0 | 81.3 |      |
|           |  |                           | $T_C = T_{C,\text{MAX}}$ | 69.0 |      |      |
|           |  |                           | $T_C = T_{C,\text{MIN}}$ | 75.0 |      |      |
|           |  | $f_{IN} = 50\text{ MHz}$  |                          | 78.1 |      |      |
|           |  | $f_{IN} = 70\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 68.0 | 82.6 |      |
|           |  |                           | $T_C = T_{C,\text{MAX}}$ | 69.0 |      |      |
|           |  |                           | $T_C = T_{C,\text{MIN}}$ | 67.0 |      |      |
|           |  | $f_{IN} = 100\text{ MHz}$ |                          | 83.3 |      |      |
|           |  | $f_{IN} = 170\text{ MHz}$ |                          | 68.0 |      |      |
|           |  | $f_{IN} = 230\text{ MHz}$ |                          | 65.4 |      |      |
|           | Worst other harmonic/spur (other than HD2 and HD3) | $f_{IN} = 10\text{ MHz}$  | Full Temp Range          | 75.0 | 85.5 | dBc  |
|           |  |                           | $T_C = 25^\circ\text{C}$ | 80.0 | 83.8 |      |
|           |  | $f_{IN} = 30\text{ MHz}$  | $T_C = T_{C,\text{MAX}}$ | 74.0 |      |      |
|           |  |                           | $T_C = T_{C,\text{MIN}}$ | 80.0 |      |      |
|           |  | $f_{IN} = 50\text{ MHz}$  |                          | 87.0 |      |      |
|           |  | $f_{IN} = 70\text{ MHz}$  | $T_C = 25^\circ\text{C}$ | 74.0 | 83.0 |      |
|           |  |                           | $T_C = T_{C,\text{MAX}}$ | 72.0 |      |      |
|           |  |                           | $T_C = T_{C,\text{MIN}}$ | 74.0 |      |      |
|           |  | $f_{IN} = 100\text{ MHz}$ |                          | 82.5 |      |      |
|           |  | $f_{IN} = 170\text{ MHz}$ |                          | 79.8 |      |      |
|           |  | $f_{IN} = 230\text{ MHz}$ |                          | 78.0 |      |      |

## ELECTRICAL CHARACTERISTICS (Unchanged after 100 kRad) (continued)

Typical values at  $T_C = 25^\circ\text{C}$ , Over full temperature range is  $T_{C,\text{MIN}} = -55^\circ\text{C}$  to  $T_{C,\text{MAX}} = 125^\circ\text{C}$ , sampling rate = 105 MSPS, 50% clock duty cycle,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$ ,  $-1\text{ dBFS}$  differential input, and  $3\text{-}V_{PP}$  sinusoidal clock (unless otherwise noted)

| PARAMETER              |                           | TEST CONDITIONS           |                                     | MIN  | TYP  | MAX  | UNIT |
|------------------------|---------------------------|---------------------------|-------------------------------------|------|------|------|------|
| THD                    | Total harmonic distortion | f <sub>IN</sub> = 10 MHz  | T <sub>C</sub> = 25°C               | 71.0 | 77.8 | dBC  |      |
|                        |                           |                           | Full Temp Range                     | 70.0 |      |      |      |
|                        |                           | f <sub>IN</sub> = 30 MHz  | T <sub>C</sub> = 25°C               | 75.0 | 77.4 |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MAX</sub> | 68.0 |      |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MIN</sub> | 73.8 |      |      |      |
|                        |                           | f <sub>IN</sub> = 50 MHz  |                                     |      | 76.7 |      |      |
|                        |                           | f <sub>IN</sub> = 70 MHz  | T <sub>C</sub> = 25°C               | 67.4 | 79.6 |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MAX</sub> | 67.2 |      |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MIN</sub> | 66.4 |      |      |      |
|                        |                           | f <sub>IN</sub> = 100 MHz |                                     |      | 79.9 |      |      |
|                        |                           | f <sub>IN</sub> = 170 MHz |                                     |      | 67.6 |      |      |
|                        |                           | f <sub>IN</sub> = 230 MHz |                                     |      | 64.1 |      |      |
| ENOB                   | Effective number of bits  | f <sub>IN</sub> = 10 MHz  | T <sub>C</sub> = 25°C               | 11.1 | 11.7 | Bits |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MAX</sub> | 11.0 |      |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MIN</sub> | 11.0 |      |      |      |
|                        |                           | f <sub>IN</sub> = 30 MHz  | T <sub>C</sub> = 25°C               | 11.2 | 11.5 |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MAX</sub> | 10.8 |      |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MIN</sub> | 11.2 |      |      |      |
|                        |                           | f <sub>IN</sub> = 70 MHz  | T <sub>C</sub> = 25°C               | 10.6 | 11.4 |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MAX</sub> | 10.4 |      |      |      |
|                        |                           |                           | T <sub>C</sub> = T <sub>C,MIN</sub> | 10.5 |      |      |      |
| RMS idle channel noise |                           | Input pins tied together  |                                     | 0.9  |      | LSB  |      |

## 4.4 DIGITAL CHARACTERISTICS (Unchanged after 100 kRad)

Typical values at  $T_C = 25^\circ\text{C}$ , Over full temperature range is  $T_{C,\text{MIN}} = -55^\circ\text{C}$  to  $T_{C,\text{MAX}} = 125^\circ\text{C}$ ,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$  (unless otherwise noted)

| PARAMETER                 | TEST CONDITIONS                 | MIN  | TYP | MAX | UNIT |
|---------------------------|---------------------------------|------|-----|-----|------|
| <b>Digital Outputs</b>    |                                 |      |     |     |      |
| Low-level output voltage  | $C_{LOAD} = 10\text{ pF}^{(1)}$ |      | 0.1 | 0.6 | V    |
| High-level output voltage | $C_{LOAD} = 10\text{ pF}^{(1)}$ | 2.6  | 3.2 |     | V    |
| Output capacitance        |                                 |      | 3   |     | pF   |
| DMID                      |                                 | 1.65 |     | 1.8 | V    |

(1) Equivalent capacitance to ground of (load + parasitics of transmission lines)

## 4.5 TIMING CHARACTERISTICS<sup>(1)</sup>(Unchanged after 100 kRad)

Typical values at  $T_C = 25^\circ\text{C}$ , Over full temperature range,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$ , sampling rate = 105 MSPS

| PARAMETER                                      |   | MIN | TYP                 | MAX | UNIT          |
|--|---|-----|---------------------|-----|---------------|
| <b>Aperture Time</b>                           |   |     |                     |     |               |
| $t_A$  | Aperture delay  |     | 500                 |     | ps            |
| $t_J$  | Clock slope independent aperture uncertainty (jitter)                         |     | 150                 |     | fs            |
| $k_J$  | Clock slope dependent jitter factor   |     | 50                  |     | $\mu\text{V}$ |
| <b>Clock Input</b>                             |   |     |                     |     |               |
| $t_{CLK}$                                      | Clock period  |     | 9.5                 |     | ns            |
| $t_{CLKH}$                                     | Clock pulse width high  |     | 4.75                |     | ns            |
| $t_{CLKL}$                                     | Clock pulse width low   |     | 4.75                |     | ns            |
| <b>Clock to DataReady (DRY)</b>                |   |     |                     |     |               |
| $t_{DR}$                                       | Clock rising 50% to DRY falling 50%   | 2.2 | 3.0                 | 4.7 | ns            |
| $t_{C\_DR}$                                    | Clock rising 50% to DRY rising 50%  |     | $t_{DR} + t_{CLKH}$ |     | ns            |
| $t_{C\_DR\_50\%}$                              | Clock rising 50% to DRY rising 50% with 50% duty cycle clock                  | 7.0 | 7.8                 | 9.5 | ns            |
| <b>Clock to DATA, OVR<sup>(2)</sup></b>        |   |     |                     |     |               |
| $t_r$  | Data $V_{OL}$ to data $V_{OH}$ (rise time)                                    |     | 0.6                 |     | ns            |
| $t_f$  | Data $V_{OH}$ to data $V_{OL}$ (fall time)                                    |     | 0.6                 |     | ns            |
| L  | Latency   |     | 3                   |     | Cycles        |
| $t_{su\_c}$                                    | Valid DATA <sup>(3)</sup> to clock 50% with 50% duty cycle clock (setup time) | 1.8 | 3.6                 |     | ns            |
| $t_{h\_c}$                                     | Clock 50% to invalid DATA <sup>(3)</sup> (hold time)                          | 2.6 | 4.1                 |     | ns            |
| <b>DataReady (DRY)/DATA, OVR<sup>(2)</sup></b> |   |     |                     |     |               |
| $t_{su(DR)\_50\%}$                             | Valid DATA <sup>(3)</sup> to DRY 50% with 50% duty cycle clock (setup time)   | 0.9 | 1.40                |     | ns            |
| $t_{h(DR)\_50\%}$                              | DRY 50% to invalid DATA <sup>(3)</sup> with 50% duty cycle clock (hold time)  | 3.9 | 6.3                 |     | ns            |

(1) All values obtained from design and characterization.

(2) Data is updated with clock rising edge or DRY falling edge.

(3) See  $V_{OH}$  and  $V_{OL}$  levels.





Figure 1. Timing Diagram



## 5 DEVICE INFORMATION



### TERMINAL FUNCTIONS


| TERMINAL                |   | DESCRIPTION  |
|-------------------------|---|--|
| NAME                    | NO.   |  |
| DRV <sub>DD</sub>       | 1, 33, 43   | 3.3 V power supply, digital output stage only                                    |
| GND                     | 2, 4, 7, 10, 13, 15, 17, 19, 21, 23, 25, 27, 29, 34, 42 | Ground   |
| VREF                    | 3   | 2.4 V reference. Bypass to ground with a 0.1 $\mu$ F microwave chip capacitor.   |
| CLK                     | 5   | Clock input. Conversion initiated on rising edge                                 |
| $\overline{\text{CLK}}$ | 6   | Complement of CLK, differential input  |
| AV <sub>DD</sub>        | 8, 9, 14, 16, 18, 22, 26, 28, 30                        | 5 V analog power supply  |
| AIN                     | 11  | Analog input   |
| $\overline{\text{AIN}}$ | 12  | Complement of AIN, differential analog input                                     |
| C1                      | 20  | Internal voltage reference. Bypass to ground with a 0.1 $\mu$ F chip capacitor.  |
| C2                      | 24  | Internal voltage reference. Bypass to ground with a 0.1 $\mu$ F chip capacitor.  |
| DNC                     | 31  | Do not connect   |
| OVR                     | 32  | Overrange bit. A logic level high indicates the analog input exceeds full scale. |
| DMID                    | 35  | Output data voltage midpoint. Approximately equal to (DV <sub>CC</sub> )/2       |
| D0 (LSB)                | 36  | Digital output bit (least significant bit); two's complement                     |
| D1–D5, D6–D12           | 37–41, 44–50  | Digital output bits in two's complement  |
| D13 (MSB)               | 51  | Digital output bit (most significant bit); two's complement                      |
| DRY                     | 52  | Data ready output  |

## 5.1 THERMAL CHARACTERISTICS

| PARAMETER       |   | TEST CONDITIONS                          | TYP   | UNIT |
|-----------------|---|--|-------|------|
| $R_{\theta JA}$ | Junction-to-free-air thermal resistance | Board Mounted, Per JESD 51-5 methodology | 21.81 | °C/W |
| $R_{\theta JC}$ | Junction-to-case thermal resistance     | MIL-STD-883 Test Method 1012             | 0.849 | °C/W |

## 6 Thermal Notes

This CQFP package has built-in vias that electrically and thermally connect the bottom of the die to a pad on the bottom of the package. To efficiently remove heat and provide a low-impedance ground path, a thermal land is required on the surface of the PCB directly underneath the body of the package. During normal surface mount flow solder operations, the heat pad on the underside of the package is soldered to this thermal land creating an efficient thermal path. Normally, the PCB thermal land has a number of thermal vias within it that provide a thermal path to internal copper areas (or to the opposite side of the PCB) that provide for more efficient heat removal. TI typically recommends a 16-mm<sup>2</sup> board-mount thermal pad. This allows maximum area for thermal dissipation, while keeping leads away from the pad area to prevent solder bridging. A sufficient quantity of thermal/electrical vias must be included to keep the device within recommended operating conditions. This pad must be electrically at ground potential.



**Figure 2. ADS5424 Estimated Device Life at Elevated Temperatures Electromigration Fail Mode**

## 7 DEFINITION OF SPECIFICATIONS

### Analog Bandwidth

The analog input frequency at which the power of the fundamental is reduced by 3 dB with respect to the low-frequency value

### Aperture Delay

The delay in time between the rising edge of the input sampling clock and the actual time at which the sampling occurs

### Aperture Uncertainty (Jitter)

The sample-to-sample variation in aperture delay

### Clock Pulse Width/Duty Cycle

The duty cycle of a clock signal is the ratio of the time the clock signal remains at a logic high (clock pulse width) to the period of the clock signal. Duty cycle is typically expressed as a percentage. A perfect differential sine wave clock results in a 50% duty cycle.

### Maximum Conversion Rate

The maximum sampling rate at which certified operation is given. All parametric testing is performed at this sampling rate unless otherwise noted.

### Minimum Conversion Rate

The minimum sampling rate at which the ADC functions

### Differential Nonlinearity (DNL)

An ideal ADC exhibits code transitions at analog input values spaced exactly 1 LSB apart. DNL is the deviation of any single step from this ideal value, measured in units of LSB.

### Integral Nonlinearity (INL)

INL is the deviation of the ADC transfer function from a best-fit line determined by a least-squares curve fit of that transfer function, measured in units of LSB.

### Gain Error

Gain error is the deviation of the ADC actual input full-scale range from its ideal value. Gain error is given as a percentage of the ideal input full-scale range.

### Offset Error

The offset error is the difference, given in number of LSBs, between the ADC's actual value average idle channel output code and the ideal average idle channel output code. This quantity is often mapped into mV.

### Temperature Drift

The temperature drift coefficient (with respect to gain error and offset error) specifies the change per degree celsius of the parameter from  $T_{MIN}$  or  $T_{MAX}$ . It is computed as the maximum variation of that parameter over the whole temperature range divided by  $T_{MAX} - T_{MIN}$ .

### Signal-to-Noise Ratio (SNR)

SNR is the ratio of the power of the fundamental ( $P_S$ ) to the noise floor power ( $P_N$ ), excluding the power at dc and in the first five harmonics.

$$SNR = 10\log_{10} \frac{P_S}{P_N}$$

SNR is given either in units of dBc (dB to carrier) when the absolute power of the fundamental is used as the reference, or dBFS (dB to full scale) when the power of the fundamental is extrapolated to the converter's full-scale range.

### Signal-to-Noise and Distortion (SINAD)

SINAD is the ratio of the power of the fundamental ( $P_S$ ) to the power of all the other spectral components including noise ( $P_N$ ) and distortion ( $P_D$ ), but excluding dc.

$$SINAD = 10\log_{10} \frac{P_S}{P_N + P_D}$$

SINAD is given either in units of dBc (dB to carrier) when the absolute power of the fundamental is used as the reference, or dBFS (dB to Full Scale) when the power of the fundamental is extrapolated to the converter's full-scale range.

### Total Harmonic Distortion (THD)

THD is the ratio of the power of the fundamental ( $P_S$ ) to the power of the first five harmonics ( $P_D$ ).

$$THD = 10\log_{10} \frac{P_S}{P_D}$$

THD is typically given in units of dBc (dB to carrier).

### Spurious-Free Dynamic Range (SFDR)

The ratio of the power of the fundamental to the highest other spectral component (either spur or harmonic). SFDR is typically given in units of dBc (dB to carrier).

### Two-Tone Intermodulation Distortion

IMD3 is the ratio of the power of the fundamental (at frequencies  $f_1$ ,  $f_2$ ) to the power of the worst spectral component at either frequency  $2f_1 - f_2$  or  $2f_2 - f_1$ . IMD3 is given either in units of dBc (dB to carrier) when the absolute power of the fundamental is used as the reference, or dBFS (dB to full scale) when it is referred to the full-scale range

## 8 TYPICAL CHARACTERISTICS

Typical values are at  $T_A = 25^\circ\text{C}$ ,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$ , differential input amplitude =  $-1\text{ dBFS}$ , sampling rate = 105 MSPS, 3 V<sub>PP</sub> sinusoidal clock, 50% duty cycle, 16k FFT points (unless otherwise noted)




Figure 3.




Figure 4.




Figure 5.




Figure 6.




Figure 7.






Figure 8.

## TYPICAL CHARACTERISTICS (continued)

Typical values are at  $T_A = 25^\circ\text{C}$ ,  $AV_{DD} = 5\text{ V}$ ,  $DRV_{DD} = 3.3\text{ V}$ , differential input amplitude =  $-1\text{ dBFS}$ , sampling rate = 105 MSPS, 3  $V_{PP}$  sinusoidal clock, 50% duty cycle, 16k FFT points (unless otherwise noted)



## 9 EQUIVALENT CIRCUITS




Figure 11. Analog Input




Figure 12. Digital Output




Figure 13. Clock Input






Figure 14. Reference

## EQUIVALENT CIRCUITS (continued)



**Figure 15. Decoupling Pin**



**Figure 16. DMID Generation**

## 10 APPLICATION INFORMATION

### 10.1 THEORY OF OPERATION


The ADS5424 is a 14-bit, 105-MSPS, monolithic pipeline analog to digital converter. Its bipolar analog core operates from a 5-V supply, while the output uses 3.3-V supply for compatibility with the CMOS family. The conversion process is initiated by the rising edge of the external input clock. At that instant, the differential input signal is captured by the input track and hold (T&H) and the input sample is sequentially converted by a series of small resolution stages, with the outputs combined in a digital correction logic block. Both the rising and the falling clock edges are used to propagate the sample through the pipeline every half clock cycle. This process results in a data latency of three clock cycles, after which the output data is available as a 14 bit parallel word, coded in binary 2's complement format.

### 10.2 INPUT CONFIGURATION


The analog input for the ADS5424 (see [Figure 11](#)) consists of an analog differential buffer followed by a bipolar track-and-hold. The analog buffer isolates the source driving the input of the ADC from any internal switching. The input common mode is set internally through a 500- $\Omega$  resistor connected from 2.4 V to each of the inputs. This results in a differential input impedance of 1 k $\Omega$ .

For a full-scale differential input, each of the differential lines of the input signal (pins 11 and 12) swings symmetrically between  $2.4 \pm 0.55$  V and  $2.4 - 0.55$  V. This means that each input is driven with a signal of up to  $2.4 \pm 0.55$  V, so that each input has a maximum signal swing of 1.1 V<sub>PP</sub> for a total differential input signal swing of 2.2 V<sub>PP</sub>. The maximum swing is determined by the internal reference voltage generator eliminating any external circuitry for this purpose.

The ADS5424 obtains optimum performance when the analog inputs are driven differentially. The circuit in [Figure 17](#) shows one possible configuration using an RF transformer with termination either on the primary or on the secondary of the transformer. If voltage gain is required, a step-up transformer can be used. For higher gains that would require impractical higher turn ratios on the transformer, a single-ended amplifier driving the transformer can be used (see [Figure 18](#)). Another circuit optimized for performance would be the one on [Figure 19](#), using the THS4304 or the OPA695. Texas Instruments has shown excellent performance on this configuration up to 10-dB gain with the THS4304 and at 14-dB gain with the OPA695. For the best performance, they need to be configured differentially after the transformer (as shown) or in inverting mode for the OPA695 (see SBAA113); otherwise, HD2 from the op amps limits the useful frequency.



**Figure 17. Converting a Single-Ended Input to a Differential Signal Using RF Transformers**



**Figure 18. Using the OPA695 With the ADS5424**



## INPUT CONFIGURATION (continued)




Figure 19. Using the THS4304 With the ADS5424

Texas Instruments offers a wide selection of single-ended operational amplifiers (including the THS3201, THS3202 and OPA847) that can be selected depending on the application. An RF gain block amplifier, such as Texas Instrument's THS9001, also can be used with an RF transformer for high input frequency applications. For applications requiring dc-coupling with the signal source, instead of using a topology with three single-ended amplifiers, a differential input/differential output amplifier like the THS4509 (see Figure 20) can be used, which minimizes board space and reduces the number of components.




Figure 20. Using the THS4509 With the ADS5424

On this configuration, the THS4509 amplifier circuit provides 10-dB of gain, converts the single-ended input to differential, and sets the proper input common-mode voltage to the ADS5424.

The 225-Ω resistors and 2.7-pF capacitor between the THS4509 outputs and ADS5424 inputs (along with the input capacitance of the ADC) limit the bandwidth of the signal to about 100 MHz (–3 dB).

For this test, an Agilent signal generator is used for the signal source. The generator is an ac-coupled 50-Ω source. A bandpass filter is inserted in series with the input to reduce harmonics and noise from the signal source.

Input termination is accomplished via the 69.8-Ω resistor and 0.22-μF capacitor to ground in conjunction with the input impedance of the amplifier circuit. A 0.22-μF capacitor and 49.9-Ω resistor is inserted to ground across the 69.8-Ω resistor and 0.22-μF capacitor on the alternate input to balance the circuit.

## INPUT CONFIGURATION (continued)

Gain is a function of the source impedance, termination, and 348-Ω feedback resistor. See the THS4509 data sheet for further component values to set proper 50-Ω termination for other common gains.

Because the ADS5424 recommended input common-mode voltage is 2.4 V, the THS4509 is operated from a single power supply input with  $V_{S+} = 5\text{ V}$  and  $V_{S-} = 0\text{ V}$  (ground). This maintains maximum headroom on the internal transistors of the THS4509.

### 10.3 CLOCK INPUTS

The ADS5424 clock input can be driven with either a differential clock signal or a single-ended clock input, with little or no difference in performance between both configurations. In low-input-frequency applications, where jitter may not be a big concern, the use of single-ended clock (see Figure 21) could save cost and board space without any trade-off in performance. When driven on this configuration, it is best to connect CLKM (pin 11) to ground with a 0.01-μF capacitor, while CLKP is ac-coupled with a 0.01-μF capacitor to the clock source, as shown in Figure 22.




Figure 21. Single-Ended Clock




Figure 22. Differential Clock

For jitter sensitive applications, the use of a differential clock has advantages (as with any other ADCs) at the system level. The first advantage is that it allows for common-mode noise rejection at the PCB level. A further analysis (see *Clocking High Speed Data Converters*, SLYT075) reveals one more advantage. The following formula describes the different contributions to clock jitter:

$$(\text{Jitter}_{\text{total}})^2 = (\text{EXT\_jitter})^2 + (\text{ADC\_jitter})^2 = (\text{EXT\_jitter})^2 + (\text{ADC\_int})^2 + (K/\text{clock\_slope})^2$$

The first term represents the external jitter, coming from the clock source, plus noise added by the system on the clock distribution, up to the ADC. The second term is the ADC contribution, which can be divided in two portions. The first does not depend directly on any external factor. The second contribution is a term inversely proportional to the clock slope. The faster the slope, the smaller this term will be. As an example, the ADC jitter contribution could be computed from a sinusoidal input clock of 3-V<sub>pp</sub> amplitude and  $F_s = 80\text{ MSPS}$ :

$$\text{ADC\_jitter} = \sqrt{((150\text{ fs})^2 + (5 \times 10^{-5} / (1.5 \times 2 \times \pi \times 80 \times 10^6))^2)} = 164\text{ fs}$$

The use of differential clock allows for the use of bigger clock amplitudes without exceeding the absolute maximum ratings. This, on the case of sinusoidal clock, results on higher slew rates, which minimize the impact of the jitter factor inversely proportional to the clock slope.

Figure 23 shows this approach. The back-to-back Schottky can be added to limit the clock amplitude in cases where this would exceed the absolute maximum ratings, even when using a differential clock.

## CLOCK INPUTS (continued)




Figure 23. Differential Clock Using PECL Logic

Another possibility is the use of a logic based clock, as PECL. In this case, the slew rate of the edges will most likely be much higher than the one obtained for the same clock amplitude based on a sinusoidal clock. This solution would minimize the effect of the slope dependent ADC jitter. Nevertheless, observe that for the ADS5424, this term is small and has been optimized. Using logic gates to square a sinusoidal clock may not produce the best results as logic gates, which may not have been optimized to act as comparators, adding too much jitter while squaring the inputs.

The common-mode voltage of the clock inputs is set internally to 2.4 V using internal 1-kΩ resistors. It is recommended to use an ac coupling, but if for any reason, this scheme is not possible, due to, for instance, asynchronous clocking, the ADS5424 presents a good tolerance to clock common-mode variation.

Additionally, the internal ADC core uses both edges of the clock for the conversion process. This means that, ideally, a 50% duty cycle should be provided.

## 10.4 DIGITAL OUTPUTS

The ADC provides 14 data outputs (D13 to D0, with D13 being the MSB and D0 the LSB), a data-ready signal (DRY, pin 52), and an out-of-range indicator (OVR, pin 32) that equals 1 when the output reaches the full-scale limits.

The output format is two's complement. When the input voltage is at negative full scale (around  $-1.1\text{V}$  differential), the output will be, from MSB to LSB, 10 0000 0000 0000. Then, as the input voltage is increased, the output switches to 10 0000 0000 0001, 10 0000 0000 0010 and so on until 11 1111 1111 1111 right before mid-scale (when both inputs are tight together if we neglect offset errors). Further increases on input voltage, outputs the word 00 0000 0000 0000, to be followed by 00 0000 0000 0001, 00 0000 0000 0010 and so on until reaching 01 1111 1111 1111 at full-scale input ( $1.1\text{V}$  differential).

Although the output circuitry of the ADS5424 has been designed to minimize the noise produced by the transients of the data switching, care must be taken when designing the circuitry reading the ADS5424 outputs. Output load capacitance should be minimized by minimizing the load on the output traces, reducing their length and the number of gates connected to them, and by the use of a series resistor with each pin. Typical numbers on the data sheet tables and graphs are obtained with 100-Ω series resistor on each digital output pin, followed by a 74AVC16244 digital buffer as the one used in the evaluation board.

## 10.5 POWER SUPPLIES

The use of low noise power supplies with adequate decoupling is recommended, being the linear supplies the first choice versus switched ones, which tend to generate more noise components that can be coupled to the ADS5424.

## POWER SUPPLIES (continued)

The ADS5424 uses two power supplies. For the analog portion of the design, a 5-V  $AV_{DD}$  is used, while for the digital outputs supply ( $DRV_{DD}$ ), we recommend the use of 3.3 V. All the ground pins are marked as GND, although AGND pins and DRGND pins are not tied together inside the package. Customers willing to experiment with different grounding schemes should know that AGND pins are 4, 7, 10, 13, 15, 17, 19, 21, 23, 25, 27, and 29, while DRGND pins are 2, 34, and 42. We recommend that both grounds are tied together externally, using a common ground plane. That is the case on the production test boards and modules provided to customer for evaluation. To obtain the best performance, user should lay out the board to assure that the digital return currents do not flow under the analog portion of the board. This can be achieved without splitting the board and with careful component placement and increasing the number of vias and ground planes.

Finally, notice that the metallic heat sink under the package is also connected to analog ground.

## 10.6 LAYOUT INFORMATION

The evaluation board represents a good guideline of how to lay out the board to obtain the maximum performance out of the ADS5424. General design rules for use of multilayer boards, single ground plane for both, analog and digital ADC ground connections, and local decoupling ceramic chip capacitors should be applied. The input traces should be isolated from any external source of interference or noise, including the digital outputs as well as the clock traces. Clock also should be isolated from other signals, especially on applications where low jitter is required, as high IF sampling.

Besides performance oriented rules, special care has to be taken when considering the heat dissipation out of the device. The thermal package information describes the  $T_{JA}$  values obtained on the different configurations.




# HFG0052B

## PACKAGE OUTLINE

CFP - 3.68 mm max height

CFP



### NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.
3. This package is hermetically sealed with a metal lid.
4. The lid and the heat sink are connected to ground leads.
5. The leads are gold plated and can be solder dipped.

## PACKAGING INFORMATION

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package<br>Qty | Eco Plan<br>(2) | Lead/Ball Finish<br>(6) | MSL Peak Temp<br>(3) | Op Temp (°C) | Device Marking<br>(4/5)              | Samples                 |
|------------------|---------------|--------------|--------------------|------|----------------|-----------------|-------------------------|----------------------|--------------|--------------------------------------|-------------------------|
| 5962-0720601VXC  | ACTIVE        | CFP          | HFG                | 52   | 1              | TBD             | Call TI                 | N / A for Pkg Type   | -55 to 125   | 5962-<br>0720601VXC<br>ADS5424MHFG-V | <a href="#">Samples</a> |
| ADS5424HFG/EM    | ACTIVE        | CFP          | HFG                | 52   | 1              | TBD             | Call TI                 | N / A for Pkg Type   | 25 Only      | ADS5424HFG/EM<br>EVAL ONLY           | <a href="#">Samples</a> |

(1) The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

**OBSELETE:** TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

**Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and

---

continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

**OTHER QUALIFIED VERSIONS OF ADS5424-SP :**

- Catalog: [ADS5424](#)

**NOTE: Qualified Version Definitions:**

- Catalog - TI's standard catalog product

## IMPORTANT NOTICE

Texas Instruments Incorporated (TI) reserves the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

TI's published terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products that TI has qualified and released to market. Additional terms may apply to the use or sale of other types of TI products and services.

Reproduction of significant portions of TI information in TI data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such reproduced documentation. Information of third parties may be subject to additional restrictions. Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyers and others who are developing systems that incorporate TI products (collectively, "Designers") understand and agree that Designers remain responsible for using their independent analysis, evaluation and judgment in designing their applications and that Designers have full and exclusive responsibility to assure the safety of Designers' applications and compliance of their applications (and of all TI products used in or for Designers' applications) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to their applications, Designer has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any applications that include TI products, Designer will thoroughly test such applications and the functionality of such TI products as used in such applications.

TI's provision of technical, application or other design advice, quality characterization, reliability data or other services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using TI Resources in any way, Designer (individually or, if Designer is acting on behalf of a company, Designer's company) agrees to use any particular TI Resource solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

Designer is authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS. TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNER AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Unless TI has explicitly designated an individual product as meeting the requirements of a particular industry standard (e.g., ISO/TS 16949 and ISO 26262), TI is not responsible for any failure to meet such industry standard requirements.

Where TI specifically promotes products as facilitating functional safety or as compliant with industry functional safety standards, such products are intended to help enable customers to design and create their own applications that meet applicable functional safety standards and requirements. Using products in an application does not by itself establish any safety features in the application. Designers must ensure compliance with safety-related requirements and standards applicable to their applications. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

TI may expressly designate certain products as completing a particular qualification (e.g., Q100, Military Grade, or Enhanced Product). Designers agree that it has the necessary expertise to select the product with the appropriate qualification designation for their applications and that proper product selection is at Designers' own risk. Designers are solely responsible for compliance with all legal and regulatory requirements in connection with such selection.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.