

LO BUFFER-AMPLIFIER

A-2050



NOTE: A-2050 is approaching EOL. Please see this letter for LTB and recommended part information.

Features

- Frequency Range 20.0 to 50.0 GHz
- 0 to +5 dBm Typical Input Power
- +20 dBm Typical Saturated Output Power

Electrical Specifications - Specifications guaranteed from -30 to +70°C, measured in a 50-Ohm system.

| Parameter | Frequency (GHz) | Min | Тур | Max |
|------------------------------|--------------------|-----|---------|-----|
| Input (dBm) | 20.0-50.0 | | 0 to +5 | |
| Saturated Output Power (dBm) | 20.0-45.0 | +15 | See | |
| | 20.0-50.0 | +12 | Plot | |
| Small Signal Gain (dB) | 20.0-50.0 | | 23 | |
| Noise Figure (dB) | 20.0-50.0 | | 7 | |
| Bias Requirements (mA) 1 | | | | |
| +5.0 Volts DC | | | 330 | 450 |
| -5.0 Volts DC | | | 5 | 20 |

¹It is required that the negative bias be applied before or concurrent with the positive bias.

| Model Number | Description | Package Style |
|-------------------|----------------------------|---------------|
| A-2050 <u>EOL</u> | 20.0 to 50.0 GHz Amplifier | <u>ESPV</u> |

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.

215 Vineyard Court, Morgan Hill, CA 95037 | Ph: 408.778.4200 | Fax 408.778.4300 | info@markimicrowave.com




LO BUFFER-AMPLIFIER


A-2050


Page 2


Frequency 20.0 to 50.0 GHz


Typical Performance














DATA SHEET NOTES:

- 1. Maximum input power without damage is +18 dBm at +70°C.
- 2. A heat sink is required for long term operation.
- 3. Specifications are subject to change without notice. Contact Marki Microwave for the most recent specifications and data sheets.

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation, or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use or application of any product.



215 Vineyard Court, Morgan Hill, CA 95037 | Ph: 408.778.4200 | Fax 408.778.4300 | info@markimicrowave.com